

2 SB 1191(A)	Mat	Si-P	=2SB1190(A):	(2SD1771	30j	(T0-220MF)	(2SB861) ⁶	17j	2SB928, (2SB630, 2SA968B, 2SB861) ⁶
2 SB 1192(A)		Si-P	=2SB1190(A):	(2SD1772	17c	SOT-186	(2SA1606) ⁷	17c	2SA1306B, 2SA1668, 2SB1096, 2SB1530
2 SB 1193	Mat	Si-P-Darl	P,120/120V, 8/12A, 50W, 15MHz, hFE=1k...20k	(2SD1773	17c	SOT-186			BD 652F, BDT 620F, 2SB1344
2 SB 1194	Mat	Si-P-Darl	P, 100/100V, 5/8A, 30W, 30MHz, hFE=1,5k...10k		17c	SOT-186	2SB1020	17c	2SB1098, 2SB1227, 2SB1258, 2SB1340
2 SB 1195	Mat	Si-P-Darl	P, 100/100V, 8A, 50W, hFE=5000		17c	SOT-186	2SB1020	17c	2SB1099...1100, 2SB1284
2 SB 1196	Hit	Si-P	LF P, 70V, 4A, 25W		15c		(BD 244 C) ³	17j	2SA1394, 2SA1469, 2SB1019, 2SB1095, ++
2 SB 1197 K	Rhm	Si-P	SMD, LF, 40/32V, 0.8A, 200MHz		35a	SOT-23			BCW 67...68
2 SB 1198 K	Rhm	Si-P	SMD, LF, 80/80V, 0.5A, 180MHz	(2SD1782	35a	SOT-23			BCX 42
2 SB 1199	Rhm	Si-P	LF, 15/15V, 0.2A, 0.3W		9c	(FTR)	BC 327	7a	BC 327...328, 2SA1515
2 SB 1201	Say	Si-P	S P, 60/50V, 2/4A, 15W, 150MHz, lo-sat<0.7V(1A)		30j	TO-251/252			-
			60/480ns	(2SD1801					
2 SB 1202	Say	Si-P	S P, 60/50V, 3/6A, 15W, 150MHz, lo-sat<0.7V(2A)		30j	TO-251/252			2SA1244
			70/485ns	(2SD1802					
2 SB 1203	Say	Si-P	S P, 60/50V, 5/8A, 20W, 130MHz, lo-sat<0.55V(3A)		30j	TO-251/252			2SA1244
			50/470ns	(2SD1803					
2 SB 1204	Say	Si-P	S P, 60/50V, 8/12A, 20W, 130MHz, lo-sat<0.5V(4A)		30j	TO-251/252			-
			50/470ns	(2SD1804					
2 SB 1205	Say	Si-P	S P, 25/20V, 5/8A, 10W, 320MHz, lo-sat<0.5V(6A)		30j	TO-251/252			-
			40/210ns						
2 SB 1206	Mat	Si-P	=2SB774: 0.3W	(2SD1807	40c		+2SB774		+2SB774
2 SB 1207	Mat	Si-P	Uni, 15/10V, 0.5/1A, 0.3W, 130MHz		40c		BC 327	7a	BC 327...328, BC 636, BC 638, BC 640, ++
2 SB 1208	Mat	Si-P	SMD, Rbe=10kΩ, LF, 20/20V, 2/2.5A, 120MHz		39b	SOT-89			(2SA1203, 2SA1314, 2SA1369, 2SA1363, ++) ¹⁸
2 SB 1209	Mat	Si-P	LF S, 400/400V, 0.1/0.2A, 1W, 70MHz		9c				2SA1363, 2SA1372, 2SA1584, 2SA1760
2 SB 1210	Rhm	Si-P	LF, 20/10V, 2A, 0.5W, 80MHz	(2SD1810	7c	TO-92	2SB892	7c(9mm)	MPS 750, 2SB733, 2SB738...739, 2SB892, ++
2 SB 1211	Rhm	Si-P	=2SB1210: SMD		39b	SOT-89			2SA1203, 2SA1314, 2SA1369, 2SA1363, ++
2 SB 1212	Rhm	Si-P	LF, 160/160V, 1.5/3A, 0.9W, 50MHz	(2SD1812	7c(9mm)	TO-92L	2SB1212	7c(9mm)	2SA1770, 2SB1130A, 2SB1236A
2 SB 1213	Hit	Si-P-Darl+Di	P, 120/120V, 10A, 30W, hFE=5000		15c				-
2 SB 1214	Say	Si-P-Darl+Di	P, 80/60V, 3/6A, 15W, hFE=5k>2k		30j	TO-251/252			2SB908, 2SB1072, 2SB1303
2 SB 1215	Say	Si-P	S P, 120/100V, 3/6A, 20W, 130MHz, lo-sat<0.5V(1.5A)		30j	TO-251/252			-
			100/850ns	(2SD1815					
2 SB 1216	Say	Si-P	S P, 120/100V, 4/8A, 20W, 130MHz, lo-sat<0.5V(2A)		30j	TO-251/252			-
			100/850ns	(2SD1816					
2 SB 1217	Nec	Si-P	P, 60/60V, 3/5A, 10W, 50MHz, <0.5/2.5μs	(2SD1818	14h	TO-126	2SB986	14h	2SB986
			lo-sat<0.3V(1.5A)						
2 SB 1218	Mat	Si-P	=2SB709:	(2SD1819	35a(2mm)	SOT-323			2SA1576, 2SA1586, 2SA1603, 2SA1622
2 SB 1218 A		Si-P	=2SB709A:		35a(2mm)	SOT-323			2SA1576, 2SA1586, 2SA1603, 2SA1622
2 SB 1219	Mat	Si-P	=2SB710:	(2SD1820	35a(2mm)	SOT-323			2SA1577, 2SA1588
2 SB 1219 A		Si-P	=2SB710A:		35a(2mm)	SOT-323			-
2 SB 1220	Mat	Si-P	=2SB792:	(2SD1821	35a(2mm)	SOT-323			2SA1609
2 SB 1221	Mat	Si-P	Vid, 250/200V, 70/100mA, 1W, 80MHz	(2SC3941	7c(9mm)	TO-92L	BF 421A	7c	BF 423A, BF 436, BF 492, 2SA1371...72, ++
2 SB 1222	Mat	Si-P	SMD, S, 40/40V, 0.2A, <300ns		35a	SOT-23			BSR 15...16, BSR 18, 2SA1338
2 SB 1223	Say	Si-P-Darl+Di	P, 70/60V, 4/6A, 20W, 20MHz, hFE=5k>2k	(2SD1825	17c	TO-220 Iso			2SB1024, 2SB1098, 2SB1282, 2SB1342, ++
2 SB 1224	Say	Si-P-Darl+Di	P, 70/60V, 7/10A, 25W, 20MHz, hFE=5k>2k	(2SD1826	17c	TO-220 Iso	2SB1020	17c	2SB1021, 2SB1099, 2SB1228, 2SB1283, ++
2 SB 1225	Say	Si-P-Darl+Di	P, 70/60V, 10/15A, 30W, 20MHz, hFE=5k>2k	(2SD1827	17c	TO-220 Iso			2SB1100, 2SB1259, 2SB1284
2 SB 1226	Say	Si-P-Darl+Di	P,110/100V, 3/5A, 20W, 20MHz, hFE=4k>1.5k	(2SD1828	17c	TO-220 Iso			2SB1340
2 SB 1227	Say	Si-P-Darl+Di	P,110/100V, 5/8A, 25W, 20MHz, hFE=4k>1.5k	(2SD1829	17c	TO-220 Iso			2SB1340, 2SB1344
2 SB 1228	Say	Si-P-Darl+Di	P,110/100V, 8/12A, 30W, 20MHz, hFE=4k>1.5k	(2SD1830	17c	TO-220 Iso			2SB1259, 2SB1344
2 SB 1229	Say	Si-P	S, 60/50V, 2/3A, 0.75W, 150MHz, lo-sat<0.4V(1A)		7c	TO-92			
			60/480ns	(2SD1835					
2 SB 1230	Say	Si-P	P, 110/100V, 15/25A, 100W, sat<0.8V(6A)	(2SD1840	18j	TO-3P			-
2 SB 1231	Say	Si-P	P, 110/100V, 25/40A, 120W, sat<0.8V(10A)	(2SD1841	18j	TO-3P			-
2 SB 1232	Say	Si-P	P, 110/100V, 40/65A, 150W, sat<0.8V(16A)	(2SD1842	18j	TO-3P			-
2 SB 1233(A)	Mat	Si-P	=2SB1192(A): 15W		~30c	(I-Type)	(2SB861) ⁶	17j	2SB768, 2SB842, 2SB928(A), 2SB1191
2 SB 1234	Say	Si-P-Darl	=2SB1235: SMD	(2SD1851	35a	SOT-23			BCV 46
2 SB 1235	Say	Si-P-Darl	LF, 80/50V, 0.2/0.4A, hFE>5000	(2SD1852	41c				
2 SB 1236	Rhm	Si-P	=2SB1130, A(M,AM): Pins = 14mm	(2SD1857	9c		+2SB1130...		+2SB1130...
2 SB 1237	Rhm	Si-P	=2SB909: Pins = 14mm	(2SD1858	9c		+2SB909		+2SB909
2 SB 1238	Rhm	Si-P	=2SB910: Pins = 14mm	(2SD1859	9c		+2SB910		+2SB910
2 SB 1239	Rhm	Si-P-Darl	=2SB1076(M): Pins = 14mm	(2SD1862	9c				+2SB1076
2 SB 1240		Si-P	=2SB911: Pins = 14mm		9c		+2SB911		+2SB911
2 SB 1241	Rhm	Si-P	Uni, 80/80V, 1A, 1W		9c	(ATV)	BC 640	7c	BC 640, 2SB647, 2SB1116A, 2SB1437, ++
2 SB 1242	Rhm	Si-P	Uni, 50/50V, 1A, 1W		9c	(ATV)	BC 640	7c	BC 327, BC 638, 2SB647, 2SB1116(A), ++
2 SB 1243	Rhm	Si-P	=2SB1066: Pins = 14mm	(2SD1864	9c	(ATV)	+2SB1066		+2SB1066
2 SB 1244	Hit	Si-P	Vid, 160/160V, 0.1A, 0.9W, 140MHz		7c(9mm)	TO-92L	BF 421 A	7c	BF 423A, BF 435, BF 491, 2SA1370...72, ++
2 SB 1245	Hit	Si-P	=2SB1244: 200/200V		7c(9mm)	TO-92L	BF 421 A	7c	BF 423A, BF 436, BF 491, 2SA1370...73, ++
2 SB 1246	Mit	Si-P	P, 40/20V, 2A, 10W		30j	TO-251/252	2SA1593	30j	2SA1241, 2SB838, 2SB1182, 2SB1201, ++
2 SB 1247	Mit	Si-P	P, 60/40V, 1.5A, 10W		30j	TO-251/252	2SA1593	30j	2SB839, 2SB957...960, 2SB1201...02, ++
2 SB 1248	Mit	Si-P	P, 110/100V, 0.8A, 10W		30j	TO-251/252	2SA1593	30j	2SA1592, 2SB844...845, 2SB959...960, ++
2 SB 1249	Mit	Si-P	P, 130/120V, 0.8A, 10W		30j	TO-251/252			2SA1225, 2SB840...842, 2SB905, 2SB1275, ++
2 SB 1250	Mat	Si-P-Darl	P, 100/80V, 3/6A, 35W, 20MHz, hFE=5k...30k	(2SD1890	17c	SOT-186			-
2 SB 1251	Mat	Si-P-Darl	P, 110/90V, 4/7A, 40W, 20MHz, hFE=5k...30k	(2SD1891	17c	SOT-186			-
2 SB 1252	Mat	Si-P-Darl	P, 120/90V, 5/8A, 45W, 20MHz, hFE=5k...30k	(2SD1892	17c	SOT-186			-
2 SB 1253	Mat	Si-P-Darl	P,130/110V, 6/10A, 50W, 20MHz, hFE=5k...30k	(2SD1893	16c	(TOP-3F)			-
2 SB 1254	Mat	Si-P-Darl	P,160/140V, 7/12A, 70W, 20MHz, hFE=5k...30k	(2SD1894	16c	(TOP-3F)			-
2 SB 1255	Mat	Si-P-Darl	P,160/140V, 8/15A, 100W, 20MHz, hFE=5k...30k	(2SD1895	16c	(TOP-3F)			-
2 SB 1256	Rhm	Si-P-Darl+Di	LF S, 100/100V, 2A, 1.2W, hFE=1k...10k		7c(9mm)	TO-92L			2SB1387, 2SB1318, 2SB1484
2 SB 1257	Sak	Si-P-Darl+Di	P, 60/60V, 4/8A, 25W, 200MHz, hFE>2000	(2SD1796	17c	TO-220 Iso			2SB1282, (2SB1098, 2SB1223, 2SB1342, ++) ⁸
2 SB 1258	Sak	Si-P-Darl+Di	P, 100/100V, 6/10A, 30W, 100MHz, hFE>1000	(2SD1785	17c	TO-220 Iso			2SB1283, (2SB1099, 2SB1228, 2SB1340, ++) ⁸
2 SB 1259	Sak	Si-P-Darl+Di	P, 120/120V, 10/15A, 30W, hFE>2000	(2SD2081	17c	TO-220 Iso			BDT 62CF, BDT 64CF
2 SB 1260	Rhm	Si-P	SMD, LF, 80/80V, 1A, 100MHz		39b	SOT-89			BCX 53, 2SA1890, 2SB803...04, 2SB1025...26
2 SB 1261(Z)	Nec	Si-P	=2SB1217: Z, TO-252		30j	TO-251			2SA1876, 2SB906, 2SB1134, 2SB1202
2 SB 1262	Hit	Si-P-Darl+Di	P, 60/60V, 4A, 25W, hFE=5000		15c				2SB1257, 2SB1223, 2SB1342
2 SB 1263	Hit	Si-P-Darl+Di	P, 60/60V, 8A, 25W, hFE=5000		15c				2SB1021...01, 2SB1099, 2SB1224
2 SB 1264	Mat	Si-P	=2SB1221: 0.6W	(2SD662	9c		BF 421 A	7c	BF 423A, BF 436...437, BF 492...493, ++
2 SB 1265	Mat	Si-P	LF, 400/400V, 0.1A, 1W		9c				2SA1024, 2SA1372, 2SA1251, 2SB1209
2 SB 1266	Say	Si-P	LF S P, 60/60V, 3/8A, 30W, 8MHz	(2SD1902	30c	(TO-220MF)	(BD 244 C) ⁶	17j	2SB929...930(A), (BD 936, BD 540A, ++) ⁶
2 SB 1267	Say	Si-P	S P, 60/30V, 8/15A, 30W, 120MHz, lo-sat<0.5V(3A)		30c	(TO-220MF)			-
			100/230ns	(2SD1903					
2 SB 1268	Say	Si-P	S P, 60/50V, 5/9A, 30W, 30MHz, lo-sat<0.4V(3A)		30c	(TO-220MF)			2SB1270, 2SB1449, 2SB1451
			100/900ns	(2SD1904					
2 SB 1269	Say	Si-P	S P, 60/50V, 7/12A, 40W, 10MHz, lo-sat<0.4V(4A)		30c	(TO-220MF)			2SB1271, 2SB1450, 2SB1452
			200/800ns	(2SD1905					