

形 名	社 名	最 大 定 格						順方向特性		逆方向特性		Ct (pF)		測定条件		t _{rr} (ns)		そ の 他 の 特 性 等	外 形
		V _{RRM}	V _R	I _{FM}	I _{O, IF}	I _{FSM}	P	I _{Fmin}	測定条件	I _{Rmax}	測定条件	typ	max	V _R (V)	typ	max			
		(V)	(V)	(mA)	(mA)	(A)	(mW)	(mA)	V _F (V)	(μA)	V _R (V)								
* 1SS237 (1)	日電		10		35*			10	0.6	0.1	5	0.8	1.0	0				NF<12.5dB (f=855MHz)	79K
1SS239	東芝		6		30			10	0.52	0.5	5	0.8		0				NF<9dB (f=800MHz) ΔVF<10mV ΔCt<0.2pF Bo=2erg	502
1SS242	東芝	5			30*			30	0.5	25	0.5	0.6		0.2				NF<12dB (f=800MHz) 色表示 青	502
* 1SS246	東芝	15	10	150	50	1	150	50	1	0.5	10	0.8	1	0	1			捺印はF4 VF=0.34V (If=1mA)	610A
1SS271	東芝		6		30			10	0.42	0.5	5							NF<9dB (f=800MHz Nif=3dB Io=1.5mA)	610F
1SS276	日立		3		30			35	0.5	50	0.5	0.8	0.5					チャナミ特コソハ-タ用	79H
* 1SS281	日電	10	10	35	35	35m		10	0.46	0.1	5	0.9	1.0	0				1SS281のA'用品	771
1SS281 (1)	日電		10		35*		200	10	0.55	100	5	1	0						771
1SS282	日電	5	5	50	50	50m		10	0.45	0.05	1	0.8	1.0	0					771
1SS283	日電	5	5	30	30	30m		30	0.5	25	0.5	0.6	0.9	0.2					771
* 1SS284	日電	10	10	30	30	30m		10	0.5	25	0.5	1	0						771
* 1SS285	日電	70	70	15	15	15m		15	1	0.2	50	1.5	2.0	0					771
1SS286	日立		25		35*			10	0.6	0.01	10		1.2	0				ΔVF<10mV, ΔCt<0.1pF	79F
1SS293	東芝	45	40	300	100	2		1	0.4	5	40		25	0		10			368D
1SS294	東芝	45	40	300	100	2		1	0.4	5	40		25	0		10			610A
1SS295	東芝	4			30			20	0.5	50	0.5							NF<20dB (f=800MHz, Io=1.5mA)	610F
1SS315	東芝	5			30			30	0.5	25	0.5							NF<10dB (f=800MHz, Io=1.5mA)	420D
1SS319	東芝	45	40	300	100	2		100	0.6	5	40		25	0		10		2素子複合	559A
1SS321	東芝	12	10	150	50	1		10	0.6	0.5	10		5	0		5		2素子セクタ-タイプ (オソトコソ)	610D
1SS322	東芝	45	40	300	100	2		10	0.6	5	40		25	0		10			205A
1SS345	三洋		55		10*		150	10	1	50	40	0.45	10					V _F <0.35V (I _F =1mA)	610A
1SS350	三洋	5			30*			30	0.5	25	0.5	0.69	0.9	0.2				V _F <0.23V (I _F =1mA)	610A
1SS351	三洋	5			30*			30	0.5	25	0.5	0.69	0.9	0.2				V _F <0.23V (I _F =1mA), 2素子直列	610F
1SS357	東芝		40		100			100	0.6	5	40		18	0				現品表示S3	420D
1SS358	三洋		55		10*			1	0.35	50	40	0.45	10					V _F <1V (I _F =30mA), 2素子直列	610F
1SS365	三洋		10		35*			10	0.58	0.2	2	0.8	0					V _F <1V (I _F =30mA)	610A
1SS366	三洋		10		35*			10	0.58	0.2	2	0.8	0					V _F <1V (I _F =30mA), 2素子直列	610F
FC804	三洋	30			200	2		200	0.55	15	15	6.3	10		10			2素子複合	498
FC805	三洋	35	30		500	5		500	0.55	30	15	16	10		10			2素子複合	498
FC806	三洋	55	50		100	2		100	0.55	15	25	4.4	10		10			2素子複合	498
FC809	三洋	30			70	2		70	0.55	5	15	3	10		10			2素子複合, 小電流整流用	498
HRW0203A	日立		30		200	2		200	0.5	50	30	40		0					610A
HSK151	日立		3		30			35	0.5	50	0.5		1.2	0.5					357A
HSM88AS	日立		10		15			10	0.58	0.2	2		0.85	0				ΔVF<10mV, ΔCt<0.1pF	610F
HSM88SR	日立		10		15			10	0.6	0.2	2		0.85	0				ΔVF<10mV, ΔCt<0.1pF	610G
HSM88WA	日立		10		15			10	0.58	0.2	2		0.85	0				2素子セクタ-タイプ (7ノットコソ), ΔVF<10mV, ΔC<0.1pF	610C
HSM88WK	日立		10		15			10	0.58	0.2	2		0.85	0				2素子セクタ-タイプ (3ノットコソ), ΔVF<10mV, ΔC<0.1pF	610D
HSM107S	日立		8	100		0.5		10	0.3	30	5							2素子直列	610F
HSM198S	日立		10		30			4.5	1	70	6		1.5	1				2素子直列, ΔVF<10mV, η>70%(40MHz)	610F
HSM276S	日立		3		30			35	0.5	50	0.5		0.9	0.5				ΔCt<0.1pF, CATVチャナミ特用	610F
HSM276SR	日立		3		30			35	0.5	50	0.5		0.9	0.5				2素子直列, ΔC<0.1pF	610G
HSR101	日立		30		35*			10	0.7	0.01	10		1.5	0				4箇組内 ΔVF<±5mV, ΔC<±0.05pF	421E
HSR276	日立		3		30			35	0.5	50	0.5		0.85	0.5				チャナミ特用	421E
HSR277	日立		35					10	1	0.05	25		1.2					rd<0.9Ω (2mA, 100MHz), P=150mW	421E
HSS100	日立		60					20	0.9	0.1	50		2.2	0				ΔVF<10mV, ΔCt<0.2pF	79F

外形 番号	A	D	E	ϕb	ℓ
503A	5MAX	2MAX	2.1MAX	0.5	20MIN
503B	8MAX	4.5MAX	4.5MAX	0.5	25MIN
503C	9	4.4	5MAX	0.8	A形 8MIN K形 20MIN
503D	12MAX	6	6		
503E	8	6	4.8	0.5	40
503F	8	8	4.8	0.7	40

外形 序号	A	B	C	ϕb	I
504A	37	12MAX	8	1	30±5
504B	37	12MAX	8	1	40±5
504C	42±1	9MAX	8.5±0.5	0.8	35MIN
504D	60	12MAX	8	1	40±5
504E	30±1	7±1	7±1	0.8	35MIN
504F	21±1	7±0.5	7±0.5	1.2	22MIN

Technical drawing of a rectangular component with dimensions and a cross-section symbol.

Dimensions (mm):

- Overall width: 2.5 ± 0.15
- Overall height: 0.9 ± 0.15
- Top flange width: 1.7 ± 0.2
- Top flange height: 0.3 ± 0.05
- Bottom flange width: 1.7 ± 0.2
- Bottom flange height: 0.3 ± 0.05
- Central hole diameter: $\varnothing 0.25 \text{ MIN}$
- Right side flange width: 0.13 ± 0.03
- Right side flange height: 0.13 ± 0.02

Section line symbol (bottom center):

① ②

The diagram shows a shaft of diameter ϕD supported by two bearings. A central hub of diameter ϕb and length A is mounted on the shaft. The distance from the center of the hub to the center of each bearing is ℓ .

外形符号	A	ϕD	ϕd	l
506A	6.5	3.5	0.8	22MIN
506B	7.5MAX	4MAX	0.65	25
506C	7MAX	3.5±0.2	0.8±0.1	26MIN
506D	7.8MAX	4.6MAX	0.8MAX	20MIN
506E	7.8MAX	5.2MAX	1.3MAX	20MIN
506F	7.8MAX	5.2MAX	1.4MAX	25MIN
506G	10	3.2	0.6	24MIN
506H	15	4.0	0.6	24MIN

外形番号	A	ϕD	$\phi \phi$	ℓ
507A	6.5 ± 0.2	2.5 ± 0.2	0.5	27MIN
507B	5.0MAX	2.8MAX	0.65MAX	20MIN
507C	5.0MAX	5.0MAX	0.8	26.7MIN
507D	5.5MAX	2.7MAX	0.6	24MIN
507E	5.5MAX	2.7MAX	0.8	24MIN

