

2 SD 1021	Si-N	Uni, 30V, 1A, 0,35W, 100MHz	40c	BC 639	7c	
2 SD 1022	Si-N-Darl	S-L, 100/100V, 5A, 30W, B>1500	17j	BD 901	17j	
2 SD 1023	Si-N-Darl+Di	S-L, 200/200V, 5A, 30W, B>1500	17j	BU 806	17j	
2 SD 1024	Si-N-Darl	S-L, 100/100V, 8A, 50W, B>1500	17j	BD 901	17j	
2 SD 1025	Si-N-Darl+Di	S-L, 200/200V, 8A, 50W, B>1500	17j	-		
2 SD 1026	Si-N-Darl+Di	S-L, 100/100V, 15A, 100W, B>1500	16j	BDW 83 C	18j	
2 SD 1027	Si-N-Darl+Di	S-L, 200/200V, 15A, 100W, B>1500	16j	-		
2 SD 1029	Si-N	NF/S-L, 60V, 4A, 40W	17j	BD 243 C	17j	
2 SD 1029 K	Si-N	=2SD1029: 100V	17j	BD 243 C		
2 SD 1030	Si-N	=2SD1010: SMD	35a	-		
2 SD 1031	Si-N-Darl	NF/S-L, 120V, 6A, 50W, B=4000	17j	-		
2 SD 1032	Si-N	NF/S-L, 60V, 4A, 60W, 0,2/1,4µs	18j	BD 245 C	18j	
2 SD 1032 A	Si-N	=2SD1032: 80V	18j	BD 245 C	18j	
2 SD 1032 B	Si-N	=2SD1032: 100V	18j	BD 245 C	18j	
2 SD 1033	Si-N	Vid-E, 200/150V, 2A, 20W, 10MHz	30j	(2SD1138)	17j	6
2 SD 1035	Si-N	S-L, 150/120/100V, 3A, 40W, 1,5MHz	17j	-		
2 SD 1036	Si-N	S-L, 150/120/100V, 15A, 150W, 1,5MHz	20j	-		
2 SD 1037	Si-N	S-L, 150/120/100V, 30A, 180W, 1,5MHz	20j	-		
2 SD 1038	Si-N	S-L, 150/120/100V, 40A, 180W, 1,5MHz	20j	-		
2 SD 1039	Si-N	=2SD1035:	22a	-		
2 SD 1040(A)	Si-N	=2SD1036: 120W	23a	-		
2 SD 1041	Si-N	=2SD1037: 200W	23a	-		
2 SD 1042	Si-N	=2SD1038:	23a	-		
2 SD 1044	Si-N-Darl+Di	S-L, 100V, 6A, 60W, B>700	18j	-		
2 SD 1044 A	Si-N-Darl+Di	=2SD1044: 170V	18j	-		
2 SD 1045	Si-N	Uni, 30V, 3A, 0,9W, 200MHz	7c(9mm)	2SD1347	7c(9mm)	
2 SD 1046	Si-N	NF/S-L, 150V, 8A, 80W, 15MHz	18j	2SC2837	18j	
2 SD 1047	Si-N	NF/S-L, 160V, 12A, 100W, 15MHz	18j	2SD1047	18j	
2 SD 1049	Si-N	NF/S-L, 120V, 25A, 80W	18j	BD 249 C	18j	
2 SD 1050(K)	Si-N-Darl+Di	NF/S-L, 100V, 10A, 80W, B>1000	20j	-		
2 SD 1051	Si-N	Uni, 50V, 1,5A, 1W, 150MHz	9c	2SD1207	7c	
2 SD 1052	Si-N	NF/S-L, hi-beta, 50V, 3A, 30W, B>250	17j	-		
2 SD 1052 A	Si-N	=2SD1052: B>400	17j	-		
2 SD 1053	Si-N	S-L, 400V, 1A, 15W	30j	(BUX 85)	17j	4
2 SD 1054	Si-N	S-L, 300/250V, 3A, 80W	23a	BUW 11 A	18j	
2 SD 1055	Si-N	Uni, 40V, 2A, 0,75W, 100MHz	9c	2SD1207	7c	
2 SD 1059	Si-N	NF/S-L, 100V, 6A, 40W	17j	BD 243 C	17j	
2 SD 1060	Si-N	lo-sat, 60V, 5A, 30W, 30MHz	17j	2SC3258	17j	
2 SD 1061	Si-N	lo-sat, 60V, 7A, 40W, 10MHz	17j	2SD1062	17j	
2 SD 1062	Si-N	lo-sat, 60V, 12A, 40W, 10MHz	17j	2SD1062	17j	
2 SD 1063	Si-N	lo-sat, 60V, 7A, 60W, 10MHz	18j	2SD1065	18j	
2 SD 1064	Si-N	lo-sat, 60V, 12A, 80W, 10MHz	18j	2SD1065	18j	
2 SD 1065	Si-N	lo-sat, 60V, 15A, 90W, 10MHz	18j	2SD1065	18j	
2 SD 1068	Si-N	S-L, TV-HA, 1000V, 10mA, 25W, 8,5MHz	17j	-		
2 SD 1069	Si-N+Di	TV-HA, 300/150V, 7A, 40W, 18MHz	17j	BU 406 D	17j	
2 SD 1070	Si-N	NF/S-L, 100V, 10A, 60W	16j	BD 245 C	18j	
2 SD 1071	Si-N-Darl	S-Reg, 450/450V, 6A, 40W, B>500	17j	2SD798	17j	
2 SD 1072	Si-N-Darl	S-Reg, 450/450V, 5A, 60W, B>500	17j	2SD798	17j	
2 SD 1073	Si-N-Darl	S-L, 300/250V, 4A, 40W, B>1000	17j	2SD798	17j	
2 SD 1074	Si-N	NF/S-L, 120V, 1A, 10W, B=160	30j	2SC4135	30j	
2 SD 1075	Si-N	=2SD1074: B=100	30j	2SC4135	30j	
2 SD 1076(L,S)	Si-N	NF/S-L, 25V, 2,5A, 20W	30j	(2SC1398)	17j	4
2 SD 1077(L,S)	Si-N	=2SD1076: 35V	30j	(2SC1398)	17j	4
2 SD 1078(L,S)	Si-N	NF/S-L, 50V, 2A, 20W	30j	2SC4135	30j	
2 SD 1079(L,S)	Si-N	=2SD1078: 80V	30j	2SC4135	30j	
2 SD 1080(L,S)	Si-N	NF/S-L, 180/120V, 1,5A, 20W	30j	(2SD1138)	17j	4