



# **B0540W**


# 0.5A SURFACE MOUNT SCHOTTKY BARRIER RECTIFIER

#### **Features**

- Low Forward Voltage Drop
- **Guard Ring Construction for Transient Protection**
- High Conductance
- Lead Free/RoHS Compliant (Note 1)
- Qualified to AEC-Q101 Standards for High Reliability

#### **Mechanical Data**

- Case: SOD-123
- Case Material: Molded Plastic. UL Flammability Classification Rating 94V-0
- Moisture Sensitivity: Level 1 per J-STD-020C
- Leads: Solderable per MIL-STD-202, Method 208
- Lead Free Plating (Matte Tin Finish annealed over Alloy 42 leadframe)
- Polarity: Cathode Band
- Marking: Date Code & Type Code, See Page 3
- Type Code: Marking: SF
- Ordering Information, See Page 3
- Weight: 0.01 grams (approximate)



	SOD-123										
Dim	Min	Max									
Α	3.55	3.85									
В	2.55	2.85									
С	1.40	1.70									
D	_	1.35									
E	0.45	0.65									
_	0.55 Typical										
G	0.25 —										
Н	0.11 T	ypical									
J	— 0.10										
	0° 8°										
All Din	nensions	in mm									

# **Maximum Ratings** @ T<sub>A</sub> = 25°C unless otherwise specified

Single phase, half wave, 60Hz, resistive or inductive load. For capacitive load, derate current by 20%.

Characteristic	Symbol	Value	Unit
Peak Repetitive Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage	V <sub>RRM</sub> V <sub>R</sub> WM V <sub>R</sub>	40	V
RMS Reverse Voltage	V <sub>R(RMS)</sub>	28	V
Average Rectified Output Current (See Figure 4)	Io	0.5	A
Non-Repetitive Peak Forward Surge Current 8.3ms single half sine-wave superimposed on rated load	I <sub>FSM</sub>	5.5	А

# **Thermal Characteristics**

Characteristic	Symbol	Тур	Max	Unit
Thermal Resistance Junction to Ambient Air (Note 2)	R <sub>JA</sub>	385		°C/W
Thermal Resistance Junction to Ambient Air (Note 3)	R JA	325	°C/W	
Operating and Storage Temperature Range	T <sub>i</sub> , T <sub>STG</sub>	-65 to +150		°C

Notes:


- 1. No purposefully added lead.
- 2. FR-4 PCB, minimum recommended pad layout per http://www.diodes.com/datasheets/ap02001.pdf.  $T_A = 25^{\circ}$  C.
- 3. Polymide PCB, minimum recommended pad layout per http://www.diodes.com/datasheets/ap02001.pdf. T<sub>A</sub> = 25° C.




# **Electrical Characteristics** @ T<sub>A</sub> = 25°C unless otherwise specified


Characteristic	Symbol	Value	Unit	Test Conditions
Minimum Reverse Breakdown Voltage (Note 4)	V <sub>(BR)R</sub>	40	V	$I_R = 20\mu A$
Maximum Forward Voltage Drop	V <sub>FM</sub>	0.510 0.620 0.460 0.610	V	$\begin{array}{ll} I_F = 0.5A, \ T_j = 25^{\circ}C \\ I_F = 1.0A, \ T_j = 25^{\circ}C \\ I_F = 0.5A, \ T_j = 100^{\circ}C \\ I_F = 1.0A, \ T_j = 100^{\circ}C \end{array}$
Maximum Leakage Current (Note 4)	la	10 20	μA	$V_R = 20V, T_j = 25^{\circ}C$ $V_R = 40V, T_j = 25^{\circ}C$
	I <sub>RM</sub>	5.0 13	mA	$V_R = 20V, T_j = 100^{\circ}C$ $V_R = 40V, T_j = 100^{\circ}C$
Total Capacitance	C <sub>T</sub>	170	pF	$f = 1MHz, V_R = 0V DC$


Notes: 4. Short duration pulse test used to minimize self-heating effect.






Reverse Voltage










# Ordering Information (Note 5)

Device	Packaging	Shipping		
B0540W-7-F	SOD-123	3000/Tape & Reel		

Notes: 5. For Packaging Details, go to our website at http://www.diodes.com/datasheets/ap02007.pdf.

# **Marking Information**



#### Date Code Key

Year	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009
Code	J	K	L	М	N	Р	R	S	Т	U	V	W

Мо	nth	Jan	Feb	March	Apr	May	Jun	Jul	Aug	Sep	Oct	Nov	Dec
Co	de	1	2	3	4	5	6	7	8	9	0	N	D

#### IMPORTANT NOTICE

Diodes, Inc. and its subsidiaries reserve the right to make changes without further notice to any product herein to make corrections, modifications, enhancements, improvements, or other changes. Diodes, Inc. does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on our website, harmless against all damages.

#### LIFE SUPPORT

The products located on our website at www.diodes.com are not recommended for use in life support systems where a failure or malfunction of the component may directly threaten life or cause injury without the expressed written approval of Diodes Incorporated.