20

40

60

80

100

Packaging Code

D

R

0.1

Insertion Loss (dB)

B1H3 2R1H

C221B1H

Packaging


180mm Paper Tape

Bulk(Bag)


M21CC

Data Sheet

EMIFIL[®] (Capacitor type) Single Circuit Type for Signal Lines NFM21C Series (0805 Size) Insertion Loss Characteristics (Main Items) Dimensions



Equivalent Circuit



■ Rated Value (□: packaging code)

| Part Number | Capacitance | Rated Current | Rated Voltage | Insulation Resistance (min.) | Operating Temperature Range |
|----------------|--------------|---------------|---------------|------------------------------|--------------------------------|
| NFM21CC220U1H3 | 22pF ±20% | 700mA | 50Vdc | 1000M ohm | -55 to +125°C |
| NFM21CC470U1H3 | 47pF ±20% | 700mA | 50Vdc | 1000M ohm | -55 to +125°C |
| NFM21CC101U1H3 | 100pF ±20% | 700mA | 50Vdc | 1000M ohm | -55 to +125°C |
| NFM21CC221R1H3 | 220pF ±20% | 700mA | 50Vdc | 1000M ohm | -55 to +125°C |
| NFM21CC471R1H3 | 470pF ±20% | 1000mA | 50Vdc | 1000M ohm | -55 to +125°C |
| NFM21CC102R1H3 | 1000pF ±20% | 1000mA | 50Vdc | 1000M ohm | -55 to +125°C |
| NFM21CC222R1H3 | 2200pF ±20% | 1000mA | 50Vdc | 1000M ohm | -55 to +125°C |
| NFM21CC223R1H3 | 22000pF ±20% | 2000mA | 50Vdc | 1000M ohm | -55 to +125°C |

Number of Circuit: 1

Continued on the following page.

6000

Minimum Quantity

4000

500

1000

100

Frequency (MHz)

This data sheet is applied for CHIP EMIFIL® used for General Electronics equipment for your design.

/Note:

1. This datasheet is downloaded from the website of Murata Manufacturing co., ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications. Therefore, please approve our product specifications or transact the approval sheet for product specifications before ordering.



<u>mnRata</u> Murata Manufacturing Co., Ltd.

http://www.murata.com/

Data Sheet

Continued from the preceding page.

■ ①Caution/Notice

Do not use products beyond the rated current and rated voltage as this may create excessive heat and deteriorate the insulation resistance.

Notice

Solderability of Tin plating termination chip might be deteriorated when low temperature soldering profile where peak solder temperature is below the Tin melting point is used. Please confirm the solderability of Tin plating termination chip before use.

2

This data sheet is applied for CHIP EMIFIL® used for General Electronics equipment for your design.

/Note:

1. This datasheet is downloaded from the website of Murata Manufacturing co., ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications. Therefore, please approve our product specifications or transact the approval sheet for product specifications before ordering.

