

2 SA 1396	Nec	Si-P	P, 100/100V, 10/20A, 30W, <0.5/2µs	{2SC3568	17c	SOT-186			BDT 96F, 2SA1443, 2SA1652, 2SA1743
2 SA 1397	Nec	Si-P	S P, 400/400V, 2/4A, 15W, 20MHz, <1/3,5µs	{2SC3569	17c	SOT-186			2SA1501, {2SA1009A, 2SA1236}³
2 SA 1398	Mit	Si-P	Uni, 25/20V, 0.7/1A, 0.9W, 180MHz	{2SC3580	7c(9mm)	TO-92L	2SB892	7c(9mm)	2SA966, 2SA1382, 2SB978, 2SB1041
2 SA 1399	Mit	Si-P	Uni, 55/50V, 0.4/0.6A, 0.9W, 150MHz	{2SC3581	7c(9mm)	TO-92L	BC 640	7c	BC 638, 2N5400...01, 2SA965, 2SA1533, ++
2 SA 1400	Nec	Si-P	S P, 400/400V, 0.5/1A, 10W, <1/6µs	{2SC3588	30j	TO-251/252	{2SA1156}⁵	14h	2SA1379, 2SA1413, 2SA1727, 2SA1772
2 SA 1401	Nec	Si-P	L.F.S P, 60/60V, 5A, 10W, <1/3,5µs		30j	TO-251/252	{BD 244 C}⁶	17j	2SA1385, 2SB1203...04, 2SB1244, {BD244A++}⁶
2 SA 1402	Say	Si-P	Vid, hi-def, 80/60V, 0.3/0.6A, 8W, 700MHz	{2SC3596	14h	TO-126	2SA1405	14h	2SA1405
2 SA 1403	Say	Si-P	Vid, hi-def, 80/60V, 0.5/1A, 10W, 800MHz	{2SC3597	14h	TO-126	2SA1403	14h	-
2 SA 1404	Say	Si-P	Vid, hi-def, 120/120V, 0.2/0.4A, 8W, 500MHz	{2SC3598	14h	TO-126	2SA1405	14h	2SA1405
2 SA 1405	Say	Si-P	Vid, hi-def, 120/120V, 0.3/0.6A, 8W, 500MHz	{2SC3599	14h	TO-126	2SA1405	14h	-
2 SA 1406	Say	Si-P	Vid, hi-def, 200/200V, 0.1/0.2A, 7W, 400MHz	{2SC3600	14h	TO-126	2SA1407	14h	2SA1407
2 SA 1407	Say	Si-P	Vid, hi-def, 200/200V, 0.15/0.3A, 7W, 400MHz	{2SC3601	14h	TO-126	2SA1407	14h	-
2 SA 1408	Tos	Si-P	CTV-VA, LF Out, 150/150V, 1.5A, 10W, 50MHz	{2SC3621	14b	TO-126iso	{2SA1249}³	14h	2SA1507, {2SA1249, 2SB649}³
2 SA 1409	Nec	Si-P	25/25V, 0.15A, 0.25W, hi-hFE=500...1600, 120/750ns		7c	TO-92	{BC 556}¹³	7a	2SA1436, {BC 213, BC 308, BC 558, ++}¹³
2 SA 1410		Si-P	=2SA1409:	{2SC3623	40c				2SA1436, {BC 213, BC 308, BC 558, ++}
2 SA 1411		Si-P	=2SA1409: SMD	{2SC3624	35a	SOT-23			{BC 856...858, BCW 29...30, BCW 69...70, ++}¹³
2 SA 1412	Nec	Si-P	P, 400/400V, 2/4A, 10W, 40MHz, <0.5/2,7µs	{2SC3631	30j	TO-251/252			2SA1773, 2SA1862
2 SA 1413	Nec	Si-P	P, 600/600V, 1/2A, 10W, 28MHz, <0.5/5,5µs	{2SC3632	30j	TO-251/252			2SA1379, 2SA1807
2 SA 1415	Say	Si-P	SMD, Uni, 180/160V, 0.14/0.2A, 150MHz	{2SC3645	39b	SOT-89			BFN 17, BFN 19
2 SA 1416	Say	Si-P	SMD, 120/100V, 1/2A, 120MHz, 80/750ns	{2SC3646	39b	SOT-89			2SA1419, 2SB1025...1028
2 SA 1417	Say	Si-P	SMD, 120/120V, 2/3A, 120MHz, 80/790ns	{2SC3647	39b	SOT-89			2SA1419, 2SB1027...28
2 SA 1418	Say	Si-P	SMD, 180/160V, 0.7/1.5A, 120MHz, 60/960ns	{2SC3648	39b	SOT-89			2SA1419, 2SB1027...1028
2 SA 1419	Say	Si-P	SMD, 180/160V, 1.5/2.5A, 120MHz, 40/740ns	{2SC3649	39b	SOT-89			2SB1027...28
2 SA 1420	Say	Si-P+R	=2SA1345: 0.4W		7c	TO-92	{BC 556}¹⁸	7a	=2SA1345
2 SA 1421	Say	Si-P+R	=2SA1346: 0.4W		7c	TO-92	{BC 556}¹⁸	7a	=2SA1346
2 SA 1422	Say	Si-P+R	=2SA1347: 0.4W		7c	TO-92	{BC 556}¹⁸	7a	=2SA1347
2 SA 1423	Say	Si-P+R	=2SA1348: 0.4W		7c	TO-92	{BC 556}¹⁸	7a	=2SA1348
2 SA 1424	Nec	Si-P	SMD, UHF, 20/12V, 0.05A, 4GHz, F=3dB(1GHz)		35a	SOT-23			-
2 SA 1425	Tos	Si-P	Uni, 120/120V, 0.8A, 1W, 120MHz	{2SC3665	9c		2SB1212	7c(9mm)	BCX 23, 2SA965, 2SA1013, 2SA1319, ++
2 SA 1426	Tos	Si-P	Uni, 35/30V, 0.8A, 1W, 120MHz	{2SC3666	9c		BC 640	7c	BC 327, BC 636, BC 638, BC 640, ++
2 SA 1427	Tos	Si-P	Uni, 30/30V, 1.5A, 1W, 120MHz		9c		2SB892	7c(9mm)	MPS750, 2SA966, 2SB819, 2SB892, 2SB978++
2 SA 1428	Tos	Si-P	Uni, 50/50V, 2A, 1W, 100MHz, 100/1100ns	{2SC3668	9c		2SB892	7c(9mm)	MPS 750...751, 2SB822, 2SB892, 2SB911, ++
2 SA 1429	Tos	Si-P	Uni, 80/80V, 2A, 1W, 80MHz, 200/1200ns	{2SC3669	9c		{2SA1593}⁴	30j	MPS 751, 2SA1315, 2SB1459
2 SA 1430	Tos	Si-P	Uni, 20/10V, 2/4A, 1W, 140MHz, lo-sat<0.5V(2A)		9c		2SB892	7c(9mm)	MPS 750, 2SB733, 2SB738...739, 2SB892, ++
2 SA 1431	Tos	Si-P	Uni, 35/20V, 5/8A, 1W, 170MHz		9c				-
2 SA 1432	Tos	Si-P	Vid, 300/300V, 0.1A, 1W, 60MHz	{2SC3672	9c		BF 421 A	7c	BF 421A, BF 437, BF 493, MPS-A92, ++
2 SA 1433	Say	Si-P	Vid, hi-def, 70/60V, 0.05A, 0.9W, 500MHz	{2SC3504	7c(9mm)	TO-92L			-
2 SA 1434	Say	Si-P	SMD, 60/50V, hi-Ueb=15V, 0.1/0.2A, 100MHz, hi-hFE=500...1200		35a	SOT-23			-
2 SA 1435	Say	Si-P	30/25V, hi-Ueb=15V, 0.3/0.5A, 0.6W, 100MHz, hi-hFE=500...1200, lo-sat<0.5V(0.2A)		7c	TO-92			-
2 SA 1436	Say	Si-P	60/50V, hi-Ueb=15V, 0.2/0.3A, 0.6W, 100MHz, hi-hFE=500...1200, lo-sat<0.5V(0.1A)		7c	TO-92			-
2 SA 1437	Say	Si-P	120/100V, hi-Ueb=15V, 50/100mA, 0.5W, 85MHz, hi-hFE=400...1000	{2SC3495	7c	TO-92			-
2 SA 1438	Say	Si-P	30/25V, hi-Ueb=15V, 1/2A, 1W, 130MHz, hi-hFE=500...1200	{2SC3070	7c(9mm)	TO-92L			-
2 SA 1440	Nec	Si-P	P, 100/60V, 3A, 15W, <300/1800ns, lo-sat	{2SC3690	17c	SOT-186			2SA1388, 2SA1441, 2SA1650, 2SA1741
2 SA 1441	Nec	Si-P	P, 100/60V, 5/10A, 25W, 80MHz, <300/1800ns, lo-sat<0.5V(4A)	{2SC3691	17c	SOT-186			2SA1388, 2SA1442, 2SA1650, 2SA1741
2 SA 1442	Nec	Si-P	P, 100/60V, 7/14A, 30W, 40MHz, <300/1800ns, lo-sat<0.5V(6A)	{2SC3692	17c	SOT-186			2SA1443, 2SA1651, 2SA1742
2 SA 1443	Nec	Si-P	P, 100/60V, 10/20A, 30W, 80MHz, <300/1800ns, lo-sat<0.5V(8A)	{2SC3693	17c	SOT-186			2SA1444, 2SA1652, 2SA1743
2 SA 1444	Nec	Si-P	P, 100/60V, 15/30A, 30W, 80MHz, <300/1800ns, lo-sat<0.5V(12A)	{2SC3694	17c	SOT-186			2SA1744
2 SA 1450	Say	Si-P	Uni, 100/80V, 0.5/0.8A, 0.6W, 120MHz	{2SC3708	7c	TO-92	BC 640	7c	BC 640, BCX 39, 2SA965, 2SB647, ++
2 SA 1451	Tos	Si-P	P, 60/50V, 12A, 30W, 70MHz, lo-sat<0.4V(6A) 300/1200ns	{2SC3709	17c	TO-220Iso	{2SB826}³	17j	2SA1568
2 SA 1452	Tos	Si-P	=2SA1451: 80/80V, 50MHz, 300/1500ns	{2SC3710	17c	TO-220Iso			-
2 SA 1453	Tos	Si-P	Uni, 50/50V, 0.1A, 0.2W, 200MHz		41c		BC 556	7a	BC 212, BC 257, BC 307, BC 557, ++
2 SA 1455 K	Rhm	Si-P	SMD, LF, In, 120/120V, 0.05A, 140MHz	{2SC3722K	35a	SOT-23			2SA1312
2 SA 1458	Nec	Si-P	S, 40/40V, 0.2A, 0.25W, 510MHz, <70/300ns	{2SC3731	40c				-
2 SA 1459	Nec	Si-P	S, 15/15V, 50/100mA, 0.25W, 1800MHz, <20/40ns		40c				-
2 SA 1460	Nec	Si-P	S, 60/45V, 1/2A, 1W, 400MHz, <40/100ns	{2SC3732	9b				-
2 SA 1461	Nec	Si-P	=2SA1458: SMD	{2SC3734	35a	SOT-23			BSR 18
2 SA 1462	Nec	Si-P	=2SA1459: SMD	{2SC3735	35a	SOT-23			BSR 12, 2SA1764
2 SA 1463	Nec	Si-P	=2SA1460: SMD	{2SC3736	39b	SOT-89			-
2 SA 1464	Nec	Si-P	SMD, HF/S, 60/40V, 0.5A, 400MHz, <35/225ns	{2SC3739	35a	SOT-23			BSS 80, BSS 82
2 SA 1465	Nec	Si-P	S, 30/25V, 1A, 0.75W, >100MHz, <1/2µs	{2SC3740	7c	TO-92			-
2 SA 1466		Si-P	=2SA1465: 0.35W	{2SC3741	40c				-
2 SA 1467		Si-P	=2SA1465: SMD	{2SC3742	35a	SOT-23			-
2 SA 1468	Hit	Si-P	SMD, HF, Vid, 180/180V, 0.1A, 200MHz		35a	SOT-23			BFN 25, 2SA1257, 2SA1330
2 SA 1469	Say	Si-P	S P, 80/60V, 5/7A, 20W, 100MHz, 100/600ns, lo-sat<0.4V(2.5A)	{2SC3746	17c	TO-220 Iso			2SA1388, {2SA1441}¹⁷
2 SA 1470	Say	Si-P	S P, 80/60V, 7/10A, 25W, 100MHz, 100/600ns, lo-sat<0.4V(3.5A)	{2SC3747	17c	TO-220 Iso			2SA1452, {2SA1442}¹⁷
2 SA 1471		Si-P	S P, 80/60V, 10/12A, 30W, 100MHz, 100/600ns, lo-sat<0.4V(5A)	{2SC3748	17c	TO-220 Iso			{2SA1444}¹⁷
2 SA 1474	Say	Si-P	Vid, hi-def, 80/60V, 0.8/1A, 15W, 800MHz	{2SC3780	17j	TO-220			-
2 SA 1475	Say	Si-P	Vid, hi-def, 120/120V, 0.4/0.6A, 15W, 500MHz	{2SC3781	17j	TO-220			-
2 SA 1476	Say	Si-P	Vid, hi-def, 200/200V, 0.2/0.3A, 15W, 400MHz	{2SC3782	17j	TO-220			-
2 SA 1477	Say	Si-P	LF Drv, 180/160V, 0.14/0.2A, 10W, 150MHz	{2SC3787	14b	TO-126 Iso	{2SA1248}³	14h	2SA1541, {BF 416, BF 418, 2SA1352...53++}³
2 SA 1478	Say	Si-P	Vid, hi-def, 200/200V, 0.1/0.2A, 5W, 150MHz	{2SC3788	14b	TO-126 Iso	{2SA1381}³	14h	2SA1541, {2SA1380...81}³
2 SA 1479	Say	Si-P	Vid, hi-def, 300/300V, 0.1/0.2A, 7W, 70MHz	{2SC3789	14b	TO-126 Iso	{2SA1381}³	14h	{2SA1353, 2SA1381}³
2 SA 1480	Say	Si-P	Vid, hi-def, 300/300V, 0.1/0.2A, 7W, 150MHz	{2SC3790	14b	TO-126 Iso	{2SA1381}³	14h	{2SA1353, 2SA1381}³
2 SA 1481	Say	Si-P	S, 60/50V, 0.15/0.4A, 0.25W, 100MHz, <290/1090ns		41c				BC 212, BC 256, BC 256, BC 556, ++
2 SA 1482	Rhm	Si-P	LF, In, 150/150V, 0.05A, 0.85W	{2SC3800	7c(9mm)	TO-92L	2SA1124	7c(9mm)	2SA1124, 2SA1482
2 SA 1483	Tos	Si-P	SMD, Uni, 60/45V, 0.2A, 200MHz, 40/280ns	{2SC3803	39b	SOT-89			-
2 SA 1484	Hit	Si-P	SMD, Uni, 90/90V, 0.1A, 130MHz		35a	SOT-23			2SA1312
2 SA 1485	Hit	Si-P	LF, Vid, 200/200V, 0.1A, 0.2W, 160MHz		7c	TO-92	BF 421 A	7c	BF 421A, BF 436...437, 2SB1349, ++